# Troubleshooting Guide

**Turn Heater on from power source.**

| Key |
| :---: |
| □ Start Question    ▢ Process Question    ■ Corrective Action |

Does the heating lamps turn on? — **No** → Are the heating lamps physically damaged? — **Yes** → Replace heating lamp(s).

**No**

Are the heating lamps wired as indicated in the manual? — **No** → Rewire lamps as indicated in this manual.

**Yes**

Find the source of the electrical problem between panel and heater.

**Yes**

Is there a sufficient amount of heat? — **No** → Is the supply voltage correct for the model type on the rating label? — **No** → Supply correct voltage

**Yes**

Is the heater mounted within the recommended height? — **Yes** → Heater size and/or quantity of heaters, may be incorrect for application.

**Yes**

Is there too much heat? — **Yes** → (to: Is the heater mounted within the recommended height?)

**No** → Mount heater within the recommended mounting heights.

**No**

**Troubleshooting ends.**

15